

深圳市宝创达电子有限公司

| 贴片共模电感                                                                              |                 |             |         |                    |              |
|-------------------------------------------------------------------------------------|-----------------|-------------|---------|--------------------|--------------|
| 产品照片                                                                                | 规格型号            | 产品尺寸 (mm)   | 电感量 (H) | 阻抗值 ( $\Omega$ )   | 额定电流 (A) max |
|    | BCCM0802-801    | 8.5*6.1*2.9 | 800u    | 3000 (at 0.8-5MHz) | 0.2          |
|    | BCCM-0904-110   | 9.5*5.6*5.2 | 11 u    | 160 (at 20-300MHz) | 0.5          |
|                                                                                     | BCCM-0904-250   | 9.5*5.6*5.2 | 25 u    | 450 (at 20-150MHz) | 0.5          |
|                                                                                     | BCCM-0904-510   | 9.5*5.6*5.2 | 51 u    | 800 (at 20-100MHz) | 0.5          |
|                                                                                     | BCCM-0904-101   | 9.5*5.6*5.2 | 100 u   | 600 (at 3-20MHz)   | 0.5          |
|                                                                                     | BCCM-0904-471   | 9.5*5.6*5.2 | 470 u   | 1200 (at 2-15MHz)  | 0.5          |
|                                                                                     | BCCM-0904-102   | 9.5*5.6*5.2 | 1 m     | 1800 (at 1-10MHz)  | 0.5          |
|                                                                                     | BCCM-0904-222   | 9.5*5.6*5.2 | 2.2 m   | 3000 (at 0.8-5MHz) | 0.5          |
|                                                                                     | BCCM-0904-472   | 9.5*5.6*5.2 | 4.7 m   | 5000 (at 0.5-3MHz) | 0.2          |
|  | BCCM-0905C-100Y | 9.2*6.0*5.0 | 10 u    | 300 (at 20~200MHz) | 1.6          |
|                                                                                     | BCCM-0905C-250Y | 9.2*6.0*5.0 | 25 u    | 600 (at 5~100MHz)  | 1            |
|                                                                                     | BCCM-0905C-400Y | 9.2*6.0*5.0 | 40 u    | 800 (at 5~100MHz)  | 0.9          |
|                                                                                     | BCCM-0905C-510Y | 9.2*6.0*5.0 | 51 u    | 1000 (at 5~10MHz)  | 0.8          |
|                                                                                     | BCCM-0905C-251Y | 9.2*6.0*5.0 | 250 u   | 600 (at 5~10MHz)   | 1.2          |
|                                                                                     | BCCM-0905C-471Y | 9.2*6.0*5.0 | 470 u   | 800 (at 1~50MHz)   | 1.1          |
|                                                                                     | BCCM-0905C-501Y | 9.2*6.0*5.0 | 500 u   | 900 (at 1~40MHz)   | 1            |
|                                                                                     | BCCM-0905C-102Y | 9.2*6.0*5.0 | 1 m     | 1000 (at 1~30MHz)  | 0.8          |
|                                                                                     | BCCM-0905C-202Y | 9.2*6.0*5.0 | 2 m     | 3000 (at 1~10MHz)  | 0.6          |
|                                                                                     | BCCM-0905C-472Y | 9.2*6.0*5.0 | 4.7 m   | 3000 (at 0.5~5MHz) | 0.4          |
|                                                                                     | BCCM-0905C-652Y | 9.2*6.0*5.0 | 6.5 m   | 4000 (at 0.3~2MHz) | 0.3          |
|  | BCDM1080-121T   | 10*8.7*6.5  | 120 u   | 460 (at 30MHz)     | 2.5          |
|                                                                                     | BCDM1080-221T   | 10*8.7*6.5  | 220 u   | 780 (at 18MHz)     | 2.2          |
|                                                                                     | BCDM1080-251T   | 10*8.7*6.5  | 250 u   | 970 (at 15MHz)     | 2.0          |
|                                                                                     | BCDM1080-471T   | 10*8.7*6.5  | 470 u   | 1750 (at 15MHz)    | 1.6          |
|                                                                                     | BCDM1080-102T   | 10*8.7*6.5  | 1 m     | 3600 (at 6.5MHz)   | 0.95         |
|  | BCDM1080-222T   | 10*8.7*6.5  | 2.2 m   | 7500 (at 4.2MHz)   | 0.75         |
|                                                                                     | BCDM1080-332T   | 10*8.7*6.5  | 3.3 m   | 8900 (at 2.0MHz)   | 0.65         |
|                                                                                     | BCDM1080-392T   | 10*8.7*6.5  | 3.9 m   | 9600 (at 2.8MHz)   | 0.52         |
|                                                                                     | BCDM1080-472T   | 10*8.7*6.5  | 4.7 m   | 13000 (at 1.0MHz)  | 0.35         |

|                                                                                     |                 |                |       |                  |      |
|-------------------------------------------------------------------------------------|-----------------|----------------|-------|------------------|------|
|    | BCDM116-2-680T  | 11.7*11.7*6.5  | 68 u  | 1500 (at 10MHz)  | 2.5  |
|                                                                                     | BCDM116-2-181T  | 11.7*11.7*6.5  | 180 u | 3000 (at 10MHz)  | 2.2  |
|                                                                                     | BCDM116-2-681T  | 11.7*11.7*6.5  | 680 u | 5000 (at 10MHz)  | 1.5  |
|                                                                                     | BCDM116-2-152T  | 11.7*11.7*6.5  | 1.5 m | 2400(at 5MHz)    | 1.2  |
|                                                                                     | BCDM116-2-222T  | 11.7*11.7*6.5  | 2.2 m | 2800(at 5MHz)    | 0.8  |
|                                                                                     | BCDM116-2-332T  | 11.7*11.7*6.5  | 3.3 m | 3900(at 2MHz)    | 0.6  |
|    | BCDM126-2-181T  | 13*10.5*6.5    | 180 u | 1500 (at 10MHz)  | 3    |
|                                                                                     | BCDM126-2-501T  | 13*10.5*6.5    | 500 u | 4200 (at 10MHz)  | 2    |
|                                                                                     | BCDM126-2-152T  | 13*10.5*6.5    | 1.5 m | 3300 (at 10MHz)  | 1.4  |
|                                                                                     | BCDM126-2-332T  | 13*10.5*6.5    | 3.3 m | 3500(at 3MHz)    | 1    |
|                                                                                     | BCDM126-2-472T  | 13*10.5*6.5    | 4.7 m | 4700(at 2MHz)    | 0.6  |
|                                                                                     | BCDM126-2-682T  | 13*10.5*6.5    | 6.8 m | 6500(at 1.5MHz)  | 0.5  |
|                                                                                     | BCDM126-2-103T  | 13*10.5*6.5    | 10 m  | 9700(at 0.8MHz)  | 0.4  |
|  | BCDM1711-2-241T | 17.5*15.8*11.5 | 240 u | 1800 (at 10MHz)  | 6.5  |
|                                                                                     | BCDM1711-2-471T | 17.5*15.8*11.5 | 470 u | 3200 (at 10MHz)  | 4.5  |
|                                                                                     | BCDM1711-2-112T | 17.5*15.8*11.5 | 1.1 m | 4600 (at 10MHz)  | 2.7  |
|                                                                                     | BCDM1711-2-302T | 17.5*15.8*11.5 | 3.0 m | 7000 (at 1MHz)   | 2    |
|                                                                                     | BCDM1711-2-472T | 17.5*15.8*11.5 | 4.7 m | 9000(at 0.8MHz)  | 1.2  |
|                                                                                     | BCDM1711-2-682T | 17.5*15.8*11.5 | 6.8 m | 12000(at 0.6MHz) | 0.8  |
|                                                                                     | BCDM1711-2-103T | 17.5*15.8*11.5 | 10 m  | 13000(at 0.4MHz) | 0.65 |
|                                                                                     | BCDM1711-2-153T | 17.5*15.8*11.5 | 15 m  | 18000(at 0.3MHz) | 0.5  |
|  | BCDM2311-2-471T | 23*22*11.5     | 470 u | 1000 (at 3MHz)   | 8    |
|                                                                                     | BCDM2311-2-821T | 23*22*11.5     | 820 u | 1800 (at 3MHz)   | 6.5  |
|                                                                                     | BCDM2311-2-152T | 23*22*11.5     | 1.5 m | 3300 (at 3MHz)   | 4.5  |
|                                                                                     | BCDM2311-2-332T | 23*22*11.5     | 3.3 m | 6500 (at 1MHz)   | 2.7  |
|                                                                                     | BCDM2311-2-682T | 23*22*11.5     | 6.8 m | 7000(at 0.8MHz)  | 1.9  |
|                                                                                     | BCDM2311-2-103T | 23*22*11.5     | 10 m  | 9000(at 0.8MHz)  | 1.6  |
|                                                                                     | BCDM2311-2-153T | 23*22*11.5     | 15 m  | 14000(at 0.3MHz) | 1.2  |